WiFi Setup Instructions

1. Download the App:



2. Open App

3. Create an Account

📶 T-Mobile 🗢	9:12 AM	7 44% 💽	.ıll T-Mobile 奈	9:12 AM Create Account	A 44% 🔲	
			⑦ Mainland Mob	ile Number Registration	n Only	Attention Installers
			Email or Phone	Number		install to your installer
L Email or Pho	ne Number		Password			account for monitoring multiple installs, you
Password		~	Confirm passwo	ard		must first make your
	6	Forget Password?	First Name			before the customer
	Sign In Create Account		Last Name	Create Account		makes their account, add the WiFi dongle to your account.
				T		
			Fill ou click '	ut this form the "Create Accour	en nt"	

4. Sign in



5. Add a Plant





capacity for your install (PV), and an income ratio (this is how much you save by producing solar power)

6. Connect your system to the internet





7. Start Monitoring



If successful, the dongle will have one red and one green light. It takes about 60sec for the lights to turn on after setup.







Password: 12345678 *Disclaimer: The wi-fi dongle does not have internet, you still need to be connected to the dongle for this process.

10:48 🍳 🖬 🖬		参 戦争 ¹¹	= al 80% ∎	1	
合 ③ 10.1	0.10.1			35	:
Device Informa	ation				
Serial Number:	E4701	1970018			
Register Key:	WSMQ	CERXVXL	RYHHS		
Hardware Version:	AEW2-	0001-02			
Software Version:	47101	19826R			
Status:					
Firmware Upgr	ade				
Choose File No f	ile chosen				
				lin	nrade
				- Op	graat
Wi-Fi Connecti	on				
Wi-Fi SSID:	wifi_te	st			
Connection	Conne	ct Fail			
<		0	111		

1. Login to Web Portal using any search browser:

a. Open Google or Safari → type in the search bar 10.10.10.1

10:48 🔍 🖬 🖬	। 🔹 📢 🗢 🖘 🗤 🕬	aii 80% 💼
Server Inform	ation	
Connection Status:	Connect Fail	
Firmware Upg	grade	
Choose File No	file chosen	
		Upgrade
Wi-Fi Connec Wi-Fi SSID:	tion wifi_test	
Status:	ellewing static ID ed	drass
Address:	0.0.0.0	liess
Netmask:	0.0.0.0	
Gateway:	0.0.0.0	
		Save Scan
		Ltd. All Right Reserved
<	0	Ш

2. Scroll Down until you see Wi-Fi Connection:

 b. Once you see the Wi-Fi connection settings, select the Scan button to search local area networks.

10:48 🔍 🗗 🖬	a 🔹 🔍 🗢 🖘 💷 🔊	0% 💼
Wi-Fi Connec	tion	
Wi-Fi SSID:	wifi_test	
Connection Status:	nection Connect Fail tus:	
Using the f	following static IP addres	ss
Address:	0.0.0	
Netmask:	0.0.0.0	
Gateway:	0.0.0.0	
		Save Scan
TP-LINK_735E		((:-
EAP-70162		(
EAP-40006		((;;
EAP-40004		(
SolArk		(
DIRECT-1d-HP	M477 LaserJet	(
CableWiFi	(
SpectrumWiFi Plus		(
EAP-70070		(
FreeMotion-20		()
<	0	111

3. You will see several networks; choose the home network (Not the dongle's network).

*Disclaimer: Connecting the dongle via the IP address only connects the dongle to the internet.

***YOU MUST STILL CREATE AN ACCOUT VIA THE POWER VIEW APP.**



- 4. Enter in the Password for your Network and select Ok
 - c. Select Network \rightarrow Enter in Password \rightarrow Select Connect

5. Once Password is Entered, tap the "Save" button underneath the Wi-Fi Information

ation			
Connect Fail			
grade			
file chosen			
	Upgrade		
tion			
wifi_test			
Connect Fail			
ollowing static IP addre	SS		
0.0.0.0			
0.0.0			
0.0.0.0			
	Save Scan		
	I Served		
	tion Connect Fail grade file chosen tion tion wifi_test Connect Fail collowing static IP addre 0.0.0.0 0.0.0.0 0.0.0.0 0.0.0.0 Commation Technology Co., Lie		

If Successful you should get a Red and Green light on the Dongle showing that it is connected.

